

RangeXtender 40



Laser receiver for all line lasers with RX-READY technology

This laser receiver is suitable for use with all red line lasers with RX-READY technology and facilitates fast alignment work at close and long range. The device detects the pulsating laser lines up to a distance of 40 metres and can be attached to measuring staffs – perfect for establishing reference dimensions. The integrated head- and side magnets allow the device to be attached to metal surfaces.

- For all red line lasers with RX-Ready technology
- Fast alignment work in close and long distance
- RX-Ready: laser lines pulsate at a high frequency
- Easily fixed to measuring staff with universal holder
- Head- and side magnets



TECHNICAL DATA

Laser Reception Range	max. 40 m
Length of Receiver Unit	20 mm
Automatic Switch-Off	after 5 minutes (if display remains unchanged)
Power Supply	2 x 1.5V LR03 (AAA)
Operating Conditions	0°C ... 40°C, max. humidity 80% rH, no condensation, max. working altitude 4000 m above sea level
Storage Conditions	-10°C ... 70°C, max. humidity 80% rH
Dimensions (W x H x D)	61 mm x 111 mm x 22 mm x (incl. battery)
Weight	150 g #



**HIGH!
SPEED!**



AutoSound

2x
AAA



SCOPE OF DELIVERY



Item No. 033.40A

GTIN (EAN) 4021563703586

SU 1