




RangeXtender 60

Laser receiver with RX-READY technology

This laser receiver is suitable for use with all red line lasers with RX-READY technology and facilitates fast alignment work at close and long range. The device saves time by detecting laser lines pulsating at high frequency up to a distance of 60 metres and can be easily attached to measuring staffs — perfect for establishing reference dimensions. The integrated head magnet allows the device to be easily attached to metal surfaces.

- For all red line lasers with RX-Ready technology
- Allows time-saving, close and long range alignment work
- RX-Ready: laser lines pulsate at a high frequency
- Detection of the laser lines up to max. 60 m
- High-Speed: very fast detection of laser lines
- Head magnet allow quick attachment to metallic surfaces
- Easily fixed to measuring staff with universal holder

TECHNICAL DATA	
Laser Reception Range	max. 60 m
Length of Receiver Unit	45 mm
Automatic Switch-Off	after 5 minutes (if display remains unchanged)
Power Supply	4 x 1.5V LR03 (AAA)
Operating Time	approx. 80 hours
Operating Conditions	-10°C 40°C, max. humidity 80% rH, no condensation, max. working altitude 4000 m above sea level
Storage Conditions	-20°C 70°C, max. humidity 80% rH
Dimensions (W x H x D)	75 mm x 148 mm x 22 mm x (without universal mount)
Weight	215 g (incl. batteries / without universal mount)


























Item No. 033.50A GTIN (EAN) 4021563710157 SU 1